

CUSTOMER SUPPORT

CrewPlex offers technical support via phone and email from 07:00 to 19:00 Central Time (UTC-06:00), Monday through Friday.

+1.334.321.1400
customer.support@crewplex.com

Visit www.crewplex.com for product support references and helpful documentation.

Additional Documentation

This is a quick start guide. For additional details on menu settings, device specifications, and product warranty, request a copy of the full DR5-900 Operating Manual by emailing customer.support@crewplex.com.

Scan this QR code with your mobile device to navigate to the Support page of our website for additional helpful resources.



IN THIS BOX

WHAT'S INCLUDED WITH DR5-900?

- Holster
- Lanyard
- USB Charging Cable
- Quick Start Guide
- Product Registration Card

ACCESSORIES

OPTIONAL ACCESSORIES

- CAC-USB6-CHG: CrewPlex 6-Port USB Charger
- ACC-USB2-CHG: Two-Port USB Vehicle Charger
- CAC-HOLSTER-M: Holster for CrewPlex DR5 BeltPack
- CAC-CPDR-5CASE: IP67-rated Hard Travel Case
- CAC-CP-SFTCASE: CrewPlex Soft Travel Case
- Selection of compatible headsets (see DR5 Manual for more details)



COPYRIGHT © 2022 CrewPlex, LLC. All rights reserved. CrewPlex™ is a trademark of CoachComm, LLC. Any and all other trademark references within this document are property of their respective owners.

Document Reference: D0000610_C

QUICK START GUIDE DR5-900



For more information visit
www.crewplex.com

SETUP

1. **Connect a headset to the BeltPack.** The BeltPack headset connection supports dual mini and single mini headsets. Dual mini connectors can be inserted in either direction. Single mini connectors can be inserted in either port of the headset connection.
2. **Power on.** Press and hold the **Power** button for three (3) seconds, until the screen turns on.

3. **Select a Group.** Press and hold the **Mode** button for 3 seconds, until the "GRP" symbol is blinking on the LCD. Then, use the **Volume +/-** buttons to select a group number from 0-51. Short-press **Mode** to save your selection and proceed to ID setting.



Figure 1: Group Edit Screen

Important: Radios must have the same group number to communicate.

4. **Select an ID.** When "ID" begins to blink on the LCD, use the **Volume +/-** buttons to select a unique ID number. Press and hold **Mode** to save your selection and exit the menu.

- a. BeltPack IDs range from 00-04.
- b. One BeltPack *must always* use the "00" ID and serve as the master BeltPack for proper system function. "MR" designates the master BeltPack on its LCD.



Figure 2: ID Edit Screen

- c. Listen-only BeltPacks must use the "L" ID. You may duplicate ID "L" on multiple BeltPacks if setting up listen-only users. (See "Receiving Mode Selection" on page 6 for more information about that process.)



Figure 3: ID Edit Screen (Master ID)

- d. Shared Talk BeltPacks must use the "Sh" ID. You may duplicate ID "Sh" on multiple BeltPacks if setting up shared users. The "Sh" ID cannot be used at the same time as the last full-duplex ID ("04").

OPERATION

- **Talk** - Use the **Talk** button to enable or disable talk for the device. "TK" appears on the LCD when enabled.
 - » For full-duplex users, use a single, short press to toggle talk on and off.
 - » For Shared Talk users ("Sh"), press and hold while talking to enable it for the device. (Only one Shared Talk user can talk at a time.)
- **Volume Up and Down** - Use the **+** and **-** buttons to control the volume. "VOL" and a numerical value from 00-09 appear on the LCD when volume is adjusted.
- **LED Modes** -
 - » Left-hand Talk/State LED is blue and double blinks when logged in and single blinks when logged out.
 - » Right-hand Charging LED is red when battery is low and also red when charging in progress. LED turns off when charging is complete.

Multiple DR5 Systems

Each separate DR5-900 system should use the same Group for all BeltPacks in that system. CrewPlex recommends that systems operating in proximity to one another set their Groups to be at least ten (10) values apart. For example, if one system is using Group 03, another system nearby should use Group 13.

Battery

- Battery life: Approx. 8 hours
- Charge time from empty: Approx. 3.5 hours
- Charging LED on BeltPack will illuminate red while charging and will turn off when charging complete.
- BeltPack may be used while charging, but doing so may lengthen charge time.

Menu Options

To access the menu, press and hold the **Mode** button for 3 seconds. Once you have finished your changes, press and hold **Mode** to save your selection and exit the menu.

Menu Setting	Default	Options	Description
Sidetone	S3	S0	Off
		S1-S5	Levels 1-5
Receiving Mode	PO	PO	Rx & Tx Mode
		PF	Rx-Only Mode (Listen-Only)
Mic Sensitivity Level	C1	C1-C5	Levels 1-5
Audio Output Level	UH	UL	Low
		UH	High

Recommended Settings by Headset

Headset Type	Recommended Setting	
	Mic Sensitivity	Audio Output
Headset with boom mic	C1	UH
Headset with lavalier mic	C3	UH