

SETUP

- Attach the beltpack antenna.** It is reverse threaded; screw counter-clockwise.
- Connect a headset to the beltpack.** Press firmly until it clicks to make sure the headset connector is seated properly.
- Power on.** Press and hold the **Power** button for 2 seconds, until the screen turns on.
- Access the menu.** Press and hold the **Mode** button for 3 seconds, until the screen changes to **<Setting Mode>**. Short-press **Mode** to scroll through the settings, and then scroll through setting options using **Volume +/-**. Press and hold **Mode** to save your selections and exit the menu.
 - Select a Group.** Select a group number from 00–51. *IMPORTANT: Beltpacks must have the same group number to communicate.*
 - Select an ID.** Select a unique ID number.
 - Repeater* Mode ID options: M, 01–08, S, or L.
 - Roam Mode ID options: M, SM, 02–09, S, or L.
 - Standard Mode ID options: M, 01–09, S, or L.
 - One beltpack *must always* use the “M” ID and serve as the master beltpack for proper system function. An “M” indicator designates the master beltpack on its OLED. (For Roam Mode, one beltpack must use the “SM” ID as well.)
 - Listen-only beltpacks must use the “L” ID. You may duplicate ID “L” on multiple beltpacks.
 - Shared beltpacks must use the “S” ID. You may duplicate ID “S” on multiple beltpacks, but only one shared beltpack may talk at a time.
 - When using “S” IDs, the last full-duplex ID cannot be used (“08” in Repeater mode and “09” in the Standard or Roam).
 - Confirm beltpack’s Security Code.** All beltpacks must use the same security code to work together as a system.

*Repeater mode is the default setting. See the DR10-900 Manual for information about modes.

OPERATION

- LED Modes** - Blue (double blink) when logged in. Blue (single blink) when logged out. Red when battery charging in progress. (LED turns off when charging is complete.)
- Lock** - To toggle between Lock and Unlock, press and hold the **Talk** and **Mode** buttons simultaneously for 3 seconds. A lock icon appears on the OLED when locked.
- Volume Up and Down** - Use the **+** and **-** buttons to control the headset volume. “Volume” and a stair-step indicator display the beltpack’s current volume setting on the OLED. You will hear a beep in your connected headset volume is changed. You will hear a different, higher-pitched beep when maximum volume is reached.
- Talk** - Use the Talk button to enable or disable talk for the device. “TALK” appears on the OLED when enabled.
 - » Latch talking: A single, short press of the button.
 - » Momentary talking: Press and hold the button for 2 seconds or longer; talk will remain on until the button is released.
 - » Shared users (“S” ID) utilize momentary talking. Only one Shared user can talk at a time.
- Mode** - Short-press the Mode button to toggle between the channels enabled on the beltpack. Long-press the Mode button to access the menu.
- Two-Way Push-to-Talk** - If you have a two-way radio connected to the master pack, you may use this button to activate Talk for the two-way radio from any pack on the system. See the DR10-900 Manual for more information about connecting a two-way radio.

Multiple DR10 Systems

Each separate DR10 system should use the same Group and Security Code for all beltpacks in that system. CrewPlex recommends that systems operating in proximity to one another set their Groups to be at least ten (10) values apart. For example, if one system is using Group 03, another system nearby should use Group 13.

Menu Options

Aside from Group and User ID, the following settings are adjustable from the beltpack menu.

Menu Setting	Default	Options
Side Tone	Off	On, Off
Mic Gain	1	1–8
Channel A	On	On, Off
Channel B*	On	On, Off
Security Code	0000	Alpha-numeric
Dual Listen	Off	On, Off
Top Button*	Off	See Manual

*Not available in Roam Mode.

Recommended Settings by Headset

Headset Type	Recommended Setting
	Mic Gain
SmartBoom LITE and PRO	1
CrewPlex Hard Hat Headset	6
CrewPlex Hard Hat LITE Headset	4
CrewPlex In-Ear Headset	7

Battery

- Battery life: Approx. 12 hours
- Charge time from empty: Approx. 3.5 hours (USB port connection) or approx. 6.5 hours (drop-in charger)
- Charging LED on beltpack will illuminate red while charging and will turn off when charging complete.
- Beltpack may be used while charging, but doing so may lengthen charge time.

Two-Way Radio Integration

The DR10 system can be integrated with a two-way radio system via the CrewPlex Two-Way I/O Headset Adapter (CRC-2WAY-IO). The DR10 system offers two basic modes of operation when interfacing and connecting to two-way radio systems. The Local mode allows users to connect to a two-way radio and keep their conversations private from the other DR10 system users. Only the DR10 user in Local mode can hear and talk to the users on the two-way system. The System mode allows a two-way radio to be connected to a DR10 system and all users can hear and talk using the connected two-way radio.

See the DR10-900 Manual and the CRC-2WAY-IO Quick Start Guide for more information on the CrewPlex Two-Way I/O Headset Adapter.

CUSTOMER SUPPORT

CrewPlex offers technical support via phone and email from 07:00 to 19:00 Central Time (UTC-06:00), Monday through Friday.

+1.334.321.1400
customer.support@crewplex.com

Visit www.crewplex.com for product support references and helpful documentation.

Additional Documentation

This is a quick start guide. For additional information, visit our support website. (Scan this QR code with your mobile device to navigate there quickly.)



IN THIS BOX

WHAT'S INCLUDED WITH DR10-900?

- BeltPack
- Li-Ion Battery (Installed during shipment)
- USB Charging Cable
- BeltPack Antenna (Attach to beltback prior to operation.)
- Quick Start Guide
- Product Registration Card

ACCESSORIES

OPTIONAL ACCESSORIES

- CAC-USB6-CHG: CrewPlex 6-Port USB Charger
- CAC-CPDR-5CASE: IP67-rated Hard Travel Case
- CAC-CP-SFTCASE: CrewPlex Soft Travel Case
- CPBT-DRC-55: CrewPlex Drop-In Charger for 5 DR10 BeltPacks and 5 Rechargeable Li-Ion Batteries
- Selection of compatible headsets (see DR10 Manual for more details)

QUICK START GUIDE DR10-900



CrewPlex

COPYRIGHT © 2022 CrewPlex, LLC. All rights reserved. CrewPlex® and SmartBoom® are trademarks of CoachComm, LLC. All other trademark references in this document are property of their respective owners.

Document Reference: D0000590_D



For more information visit
www.crewplex.com